

## ESP-200 PUMP PANEL CHART FOR ABOVE GROUND MOTORS

HP	VOLTS	FLA	SIZE	PANEL NUMBER	ESP RANGE	FUSE	OPTIONAL O/L IF YOU DO NOT WANT TO LOOP	
1HP	230V	4.2	SZ-1	87DUD6LC	5.5-22A	TR5	48ATC3S00	3-12A
1HP	460V	2.1	SZ-1	87DUD6FC	5.5-22A	TRS3	48ATB3S00	.75-3A
1.5HP	230V	6	SZ-1	87DUD6LC	5.5-22A	TR7		
1.5HP	460V	3	SZ-1	87DUD6FC	5.5-22A	TRS5	48ATC3S00	3-12A
2HP	230V	6.8	SZ-1	87DUD6LC	5.5-22A	TR8	48ATC3S00	3-12A
2HP	460V	3.4	SZ-1	87DUD6FC	5.5-22A	TRS5	48ATC3S00	3-12A
3HP	230V	9.6	SZ-1	87DUD6LC	5.5-22A	TR15		
3HP	460V	4.8	SZ-1	87DUD6FC	5.5-22A	TRS6	48ATC3S00	3-12A
5HP	230V	15.2	SZ-1	87DUE6LC	10-40A	TR20		
5HP	460V	7.6	SZ-1	87DUD6FC	5.5-22A	TRS10		
7.5HP	230V	22	SZ-1	87DUE6LC	10-40A	TR30		
7.5HP	460V	11	SZ-1	87DUD6FC	5.5-22A	TRS15		
10HP	230V	28	SZ-1.75	87EUE6LC	10-40A	TR35		
10HP	460V	14	SZ-1	87DUD6FC	5.5-22A	TRS20		
15HP	230V	42	SZ-2	87FUF6LC	13-52A	TR50		
15HP	460V	21	SZ-1.75	87EUE6FC	10-40A	TRS30		
20HP	230V	54	SZ-2.5	87GUG6PC	25-100A	TR70		
20HP	460V	27	SZ-2	87FUF6FC	13-52A	TRS35		
25HP	230V	68	SZ-3	87HUG6LC	25-100A	TR80		
25HP	460V	34	SZ-2	87FUF6FC	13-52A	TRS50		
30HP	230V	80	SZ-3	87HUG6LC	25-100A	TR100		
30HP	460V	40	SZ-2.5	87GUG6FC	13-52A	TRS60		
40HP	230V	104	SZ-3.5	87IUH6LC	50-200A	TR150		
40HP	460V	52	SZ-3	87HUG6FC	25-100A	TRS70		
50HP	230V	130	SZ-4	87JUH6LC	50-200A	TR175		
50HP	460V	65	SZ-3	87HUG6FC	25-100A	TRS90		
60HP	230V	154	SZ-5	87LPU6LG	55-250A	TR225		
60HP	460V	77	SZ-3.5	87IUH6FC	50-200A	TRS110		
75HP	230V	192	SZ-5	87LPU6LG	55-250A	TR225		
75HP	460V	96	SZ-3.5	87IUH6FC	50-200A	TRS125		
100HP	460V	124	SZ-4	87JHU6FC	50-200A	TRS175		
125HP	460V	156	SZ-5	87LPU6FH	55-250A	TRS225		
150HP	460V	180	SZ-5	87LPU6FH	55-250A	TRS250		
200HP	460V	240	SZ-5	87LPU6FH	55-250A	TRS300		



**1-800-289-2224**